

## AMENDMENTS TO THE CLAIMS

This listing of claims replaces all prior versions and listing of claims in the application.

### Listing of Claims:

1-13 (canceled).

14 (new). A driving circuit that drives a display panel having an electrode, comprising:

a first switching element that supplies a charge from a recovering capacitor to the electrode of the display panel;

an interconnector connected to said first switching element through a first one-way conductive element;

a second switching element that recovers the charge from the electrode of the display panel to said recovering capacitor;

a second one-way conductive element provided between said second switching element and said interconnector; and

a frequency reducer connected in parallel with said first switching element, that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said first switching element, and an inductance component of said interconnector, wherein the

charge is supplied to the electrode of the display panel from said recovering capacitor through said first switching element and said interconnector.

15 (new). A driving circuit that drives a display panel having an electrode, comprising:

a first switching element that supplies a charge from a recovering capacitor to the electrode of the display panel;

an interconnector connected to said first switching element through a first one-way conductive element;

a second switching element that recovers the charge from the electrode of the display panel to said recovering capacitor;

a second one-way conductive element provided between said second switching element and said interconnector; and

a frequency reducer connected in parallel with said second switching element that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said second switching element and an inductance component of said interconnector, wherein the charge is recovered to said recovering capacitor from the electrode of the display panel through said second switching element and said interconnector.

16 (new). A driving circuit that drives a display panel having an electrode, comprising:

a first switching element that supplies a charge from a recovering capacitor to the electrode of the display panel;

an interconnector connected to said first switching element through a first one-way conductive element;

a second switching element that recovers the charge from the electrode of the display panel to said recovering capacitor;

a second one-way conductive element provided between said second switching element and said interconnector;

a frequency reducer connected in parallel with said first switching element that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said first switching element and an inductance component of said interconnector; and

a frequency reducer connected in parallel with said second switching element that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said second switching element and an inductance component of said interconnector, wherein the charge is supplied to the electrode of the display panel from said recovering capacitor through said first switching element and said interconnector, and the charge is recovered to said recovering capacitor from the electrode of the display panel through said second switching

element and said interconnector.

17 (new). A driving circuit that drives a display panel having an electrode, comprising:

a first switching element that supplies a charge from a recovering capacitor to the electrode of the display panel;

an interconnector connected to said first switching element through a first one-way conductive element;

a second switching element that recovers the charge from the electrode of the display panel to said recovering capacitor;

a second one-way conductive element provided between said second switching element and said interconnector; and

a capacitor connected in parallel with said first switching element that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said first switching element and an inductance component of said interconnector, wherein the charge is supplied to the electrode of the display panel from said recovering capacitor through said first switching element and said interconnector.

18 (new). A driving circuit that drives a display panel having an electrode, comprising:

a first switching element that supplies a charge from a recovering

capacitor to the electrode of the display panel;

an interconnector connected to said first switching element through  
a first one-way conductive element;

a second switching element that recovers the charge from the  
electrode of the display panel to said recovering capacitor;

a second one-way conductive element provided between said  
second switching element and said interconnector; and

a capacitor connected in parallel with said second switching element  
that is operable to reduce a resonance frequency of an LC resonance  
resulting from a parasitic capacitance of said second switching element  
and an inductance component of said interconnector, wherein the charge is  
recovered to said recovering capacitor from the electrode of the display  
panel through said second switching element and said interconnector.

19 (new). A driving circuit that drives a display panel having an  
electrode, comprising:

a first switching element that supplies a charge from a recovering  
capacitor to the electrode of the display panel;

an interconnector connected to said first switching element through  
a first one-way conductive element;

a second switching element that recovers the charge from the  
electrode of the display panel to said recovering capacitor;

a second one-way conductive element provided between said second switching element and said interconnector; and

a first capacitor connected in parallel with said first switching element that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said first switching element and an inductance component of said interconnector; and

a second capacitor connected in parallel with said second switching element that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said second switching element and an inductance component of said interconnector, wherein the charge is supplied to the electrode of the display panel from said recovering capacitor through said first switching element and said interconnector, and the charge is recovered to said recovering capacitor from the electrode of the display panel through said second switching element and said interconnector.

20 (new). A driving circuit that drives a display panel having an electrode, comprising:

a first transistor that supplies a charge from a recovering capacitor to the electrode of the display panel;

an interconnector connected to said first transistor through a first diode;

a second transistor that recovers the charge from the electrode of the display panel to said recovering capacitor;

a second diode provided between said second transistor and said interconnector; and

a capacitor connected in parallel with a source and a drain of said first transistor that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said first transistor and an inductance component of said interconnector, wherein the charge is supplied to the electrode of the display panel from said recovering capacitor through said first transistor and said interconnector.

21 (new). A driving circuit that drives a display panel having an electrode, comprising:

a first transistor that supplies a charge from a recovering capacitor to the electrode of the display panel;

an interconnector connected to said first transistor through a first diode;

a second transistor that recovers the charge from the electrode of the display panel to said recovering capacitor;

a second diode provided between said second transistor and said interconnector; and

a capacitor connected in parallel with a source and a drain of said

second transistor that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said second transistor and an inductance component of said interconnector, wherein the charge is recovered to said recovering capacitor from the electrode of the display panel through said second transistor and said interconnector.

22 (new). A driving circuit that drives a display panel having an electrode, comprising:

- a first transistor that supplies a charge from a recovering capacitor to the electrode of the display panel;

- an interconnector connected to said first transistor through a first diode;

- a second transistor that recovers the charge from the electrode of the display panel to said recovering capacitor;

- a second diode provided between said second transistor and said interconnector; and

- a first capacitor connected in parallel with a source and a drain of said first transistor that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said first transistor and an inductance component of said interconnector; and

- a second capacitor connected in parallel with a source and a drain of said second transistor that is operable to reduce a resonance frequency



of an LC resonance resulting from a parasitic capacitance of said second transistor and an inductance component of said interconnector, wherein the charge is supplied to the electrode of the display panel from said recovering capacitor through said first transistor and said interconnector, and the charge is recovered to said recovering capacitor from the electrode of the display panel through said second transistor and said interconnector.

23 (new). A display device, comprising:

a display panel having an electrode; and

a driver that drives said electrode of said display panel, said driver comprising:

a first switching element that supplies a charge from a recovering capacitor to said electrode of said display panel;

an interconnector connected to said first switching element through a first one-way conductive element;

a second switching element that recovers the charge from said electrode of said display panel to said recovering capacitor;

a second one-way conductive element provided between said second switching element and said interconnector; and

a frequency reducer connected in parallel with said first switching element that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said first switching

element and an inductance component of said interconnector, wherein the charge is supplied to said electrode of said display panel from said recovering capacitor through said first switching element and said interconnector.

24 (new). A display device, comprising:

a display panel having an electrode; and

a driver that drives said electrode of said display panel, said driver comprising:

a first switching element that supplies a charge from a recovering capacitor to said electrode of said display panel;

an interconnector connected to said first switching element through a first one-way conductive element;

a second switching element that recovers the charge from said electrode of said display panel to said recovering capacitor;

a second one-way conductive element provided between said second switching element and said interconnector; and

a frequency reducer connected in parallel with said second switching element that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said second switching element and an inductance component of said interconnector, wherein the charge is recovered to said recovering capacitor from said

electrode of said display panel through said second switching element and said interconnector.

25 (new). A display device, comprising:

a display panel having an electrode; and

a driver that drives said electrode of said display panel, said driver comprising:

a first switching element that supplies a charge from a recovering capacitor to said electrode of said display panel;

an interconnector connected to said first switching element through a first one-way conductive element;

a second switching element that recovers the charge from said electrode of said display panel to said recovering capacitor;

a second one-way conductive element provided between said second switching element and said interconnector;

a frequency reducer connected in parallel with said first switching element that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said first switching element and an inductance component of said interconnector; and

a frequency reducer connected in parallel with said second switching element that is operable to reduce a resonance frequency of an LC resonance resulting from a parasitic capacitance of said second

switching element and an inductance component of said interconnector, wherein the charge is supplied to said electrode of said display panel from said recovering capacitor through said first switching element and said interconnector, and the charge is recovered to said recovering capacitor from said electrode of said display panel through said second switching element and said interconnector.